











## Modulera

Modular UPS 3 Phase In - 3 Phase Out / 20 - 200 kVA

- Hot Swappable Decentralized Parallel Architecture
- DSP (Digital Signal Processor) Controlled Technology
- Modular N+X Parallel Redundancy
- Plug & Play Type Hot Swappable Power Modules
- Cold Start Function
- Parallel connection availability of UPS Frames up to 4pcs
- Wide Input Voltage Window (208Vac ~ 478Vac)
- Wide input frequency range (40Hz 70Hz)
- High Overall Efficiency (up to 94%)
- Increased Output Power Factor (0.9)
- Unity Input Power Factor (0.99)
- Low Input Total Harmonic Distortion Level (THDi down to 3 %)
- Fit into standard 19" Rack Cabinet
- Touch-screen LCD display for user's friendly operation
- EPO (Emergency Power Off)
- Smart Fan Speed Control
- Programmable Battery Voltage (32/34/36/38/40 blocks of 12V Batteries)
- Three Level Battery Charge system with smart charge current adjustment
- Powerful charger built in each Modular UPS Power Module
- Equip with Maintenance Bypass Switch for easy maintenance
- RS232 & 485 Ports as standard communication
- Megatec/Mod Bus protocol supported
- Optional Communication Interfaces (SNMP Card or DRY contact board)

















## Modulera

## **TECHNICAL SPECIFICATIONS**

Frame Capacity		MDL 3300-60K	MDL 3300-100K	MDL 3300-200K	
		20kVA (18kW) to 60kVA (54kW)	20kVA (18kW) to 100kVA (90kW)	20kVA (18kW) to 200kVA (180kW)	
MDL Module Capac	city		20KVA/18KW		
NPUT					
Phase		3 Phase + Neutral + Ground			
Rated Voltage		380 / 400 / 415Vac			
Voltage Range		208 - 478Vac at 50% load, 305 - 478Vac at 100% load			
Frequency range		40Hz - 70Hz			
Power Factor		≥ 0.99			
Current THDi		down to 3%			
Generator Input		Present			
DUTPUT					
Phase			3 Phase + Neutral + Ground		
Rated Voltage		380/400/415Vac			
Power Factor		0,9			
Voltage Regulation			±1%		
vottage Negatation	Utility Mode	±1%, ±2%, ±4%, ±5%, ±10% of the rated frequency(optional)			
Frequency		(50/60 ±%0.2)Hz			
Proof Forter	Battery Mode	(50/60 ±%0.2)Hz			
Crest Factor		- Ti			
THDv		≤2% with linear load			
Waveform		Pure Sinewave 100% - 110% - 60min 110% - 125% - 150% - 150% - 150% - 1min			
	AC Mode	100% - 110%: 60min,110% - 125%: 10min, 125% - 150%: 1min, >150%: immediately transfers to bypass			
Over Load	Dot Mad	> 150%: immediately transfers to bypass 100% - 110%: 60min,110% - 125%: 10min, 125% - 150%: 1min,			
5.51 E000	Bat. Mode	>150%: immediately shutdown			
	Bypass Mode	Breaker (40Amp)			
AC-AC Efficiency		Up to 94%			
Eco-Mode Efficiency		97%			
BATTERY					
Туре			Maintenance-free lead acid batteries		
Quantity (12V VRLA batteries)		Configurable to 32/34/36/38/40 pcs per string			
Voltage (12V VRLA batteries)		384/408/432V/456V/480V DC			
Charging Current	Frame	18A Max. (charge current can be set according to battery capacity installed)	30A Max. (charge current can be set according to battery capacity installed)	60A Max. (charge current can be set according to battery capacity	
	MDL Module	, , ,	current can be set according to battery cap	installed) pacity installed)	
DISPLAY					
DISFLAI		Line Mode, Eco Mode, Bypass Mode, Battery Low, Battery Bad, Overload & UPS Fault			
			Input Voltage, Input Frequency, Output Voltage, Output Frequency, Load Percentage, Battery Voltage & Inner Tempera-		
Status LED & LCD	 D			1-1	
Status LED & LCD Reading On the LCI	D		ture		
Status LED & LCD Reading On the LCI PROTECTION	D		ture		
Status LED & LCD Reading On the LCI PROTECTION Short Circuit	D	Input Voltage, Input Frequency, Output V	ture Hold Whole System		
Status LED & LCD Reading On the LCI PROTECTION Short Circuit Overheat	D	Input Voltage, Input Frequency, Output V	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP		
Status LED & LCD Reading On the LCI PROTECTION Short Circuit Overheat Battery Low	D	Input Voltage, Input Frequency, Output V	ture Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off		
Status LED & LCD Reading On the LCI PROTECTION Short Circuit Overheat Battery Low Self-diagnostics	D	Input Voltage, Input Frequency, Output V	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP  Alarm and Switch off  Upon Power On and Software Control		
Reading On the LCI PROTECTION Short Circuit Overheat Battery Low Self-diagnostics	D	Input Voltage, Input Frequency, Output V	ture Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off		
Status LED & LCD Reading On the LCI PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional)	D	Input Voltage, Input Frequency, Output V	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP  Alarm and Switch off  Upon Power On and Software Control		
Reading On the LCD  Reading On the LCD  PROTECTION  Short Circuit  Overheat  Battery Low  Self-diagnostics  EPO (optional)  Battery	D	Input Voltage, Input Frequency, Output V	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP  Alarm and Switch off  Upon Power On and Software Control  Shut down UPS immediately		
Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression	D	Input Voltage, Input Frequency, Output V  Line Mode: Switch	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off  Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management	S immediately	
Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms	D	Input Voltage, Input Frequency, Output V  Line Mode: Switch	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off  Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2	S immediately	
Reading On the LCD  Reading On the LCD  PROTECTION  Short Circuit  Overheat  Battery Low  Self-diagnostics  EPO (optional)  Battery  Noise Suppression  Alarms  COMMUNICATION	D	Input Voltage, Input Frequency, Output V  Line Mode: Switch	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off  Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2	S immediately	
Reading On the LCD  Reading On the LCD  PROTECTION  Short Circuit  Overheat  Battery Low  Self-diagnostics  EPO (optional)  Battery  Noise Suppression  Alarms  COMMUNICATION  Standard	D	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off  Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Fai	S immediately  ult  port, 2xCommunication Slot	
Reading On the LCD  Reading On the LCD  PROTECTION  Short Circuit  Overheat  Battery Low  Self-diagnostics  EPO (optional)  Battery  Noise Suppression  Alarms  COMMUNICATION  Standard  Optional	D	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	ture  Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off  Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Fat	S immediately  ult  port, 2xCommunication Slot	
Reading On the LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional ENVIRONMENT		Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	ture  Hold Whole System  h to Bypass; Backup Mode: Shut down UP Alarm and Switch off  Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Failure, Battery Low, Overload, Battery	S immediately  ult  port, 2xCommunication Slot	
Reading On the LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional Deprating Tempera	ıture	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	ture  Hold Whole System  h to Bypass; Backup Mode: Shut down UP Alarm and Switch off  Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Failure, Battery Low, Overload, Battery	S immediately  ult  port, 2xCommunication Slot	
Reading On the LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional ENVIRONMENT Operating Temperat	ıture	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	Hold Whole System  h to Bypass; Backup Mode: Shut down UP Alarm and Switch off Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Fau 2xRS485 Communication ports, 1xModBus (Megatec Protocol), Dry Contact Board, E  0°C - 40°C -25°C - 55°C	S immediately  ult  port, 2xCommunication Slot	
Reading On the LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional ENVIRONMENT Operating Tempera Storage Temperatu Humidity	ıture	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	Hold Whole System  h to Bypass; Backup Mode: Shut down UP Alarm and Switch off Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Fau ExRS485 Communication ports, 1xModBus (Megatec Protocol), Dry Contact Board, E  0°C - 40°C -25°C - 55°C 0 - %95 non condensing	S immediately  ult  port, 2xCommunication Slot	
Status LED & LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional ENVIRONMENT Operating Tempera Storage Temperatu Humidity Altitude	ıture	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	Hold Whole System  h to Bypass; Backup Mode: Shut down UP Alarm and Switch off Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Failure, Battery Low, Overload, Battery L	S immediately  ult  port, 2xCommunication Slot	
Reading On the LCD Reading On the LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional ENVIRONMENT Operating Tempera Storage Temperatu Humidity Altitude Noise	iture Ire	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	Hold Whole System  h to Bypass; Backup Mode: Shut down UP Alarm and Switch off Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Fau ExRS485 Communication ports, 1xModBus (Megatec Protocol), Dry Contact Board, E  0°C - 40°C -25°C - 55°C 0 - %95 non condensing	S immediately  ult  port, 2xCommunication Slot	
Reading On the LCD Reading On the LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional ENVIRONMENT Operating Tempera Storage Temperatu Humidity Altitude Noise	iture ire	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Failure, Battery Low,	S immediately  ult  port, 2xCommunication Slot	
Reading On the LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional ENVIRONMENT Operating Tempera Storage Temperatu Humidity Altitude Noise PHYSICAL SPECIF Dimesions	iture ire ICATIONS	Line Mode: Switch  Line Mode: Switch  Line F  1xRS232 Communication port, 2  SNMP	Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Fat exception of the System State of the System Fat O'C A Good System Fat O'C	S immediately  ult  port, 2xCommunication Slot PO	
Status LED & LCD	iture ire	Input Voltage, Input Frequency, Output V  Line Mode: Switch  Line Frequency, Output V  Line Mode: Switch	Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Fat exception of the System State of the System Fate for Compliance of the System	S immediately  ult  port, 2xCommunication Slot	
Status LED & LCD Reading On the LCD PROTECTION Short Circuit Overheat Battery Low Self-diagnostics EPO (optional) Battery Noise Suppression Alarms COMMUNICATION Standard Optional ENVIRONMENT Operating Tempera Storage Temperatu Humidity Altitude Noise PHYSICAL SPECIF Dimesions	iture ire ICATIONS	Line Mode: Switch  Line Mode: Switch  Line F  1xRS232 Communication port, 2  SNMP	Hold Whole System h to Bypass; Backup Mode: Shut down UP Alarm and Switch off Upon Power On and Software Control Shut down UPS immediately Advanced Battery Management Complies with EN62040-2 Failure, Battery Low, Overload, System Fat exception of the System State of the System Fat O'C A Good System Fat O'C	S immediately  ult  port, 2xCommunication Slot PO	